

**Betriebsdaten:**  
Typical operation:  
Exemple d'utilisation:

$U_f$  . . . 6.3 V  
 $I_f$  . . . 0.6 A  
 $U_a$  . . . +250 V=  
 $U_{g1}$  . . . -27.5 V=  
 $I_a$  . . . 9 mA  
 $S$  . . . 1.7 mA/V  
 $D$  . . . 17 %  
 $g$  . . . 6  
 $R_i$  . . . 3.5 k $\Omega$   
 $R_{aa}$  . . . 14 k $\Omega$

**Grenzdaten:**

Ratings / Conditions maxima:  
 $\eta$  . . . 1.6 W  
 $U_{fk}$  . . . 90 V

**Prüfdaten:**

Test operation:

Vérification:

$U_f$  . . . 6.3 V~  
 $U_a$  . . . +150 V=  
 $U_{g1}$  . . . 0 & -2 V=



In Stellung 13  
auf Steuerwirkung  
prüfen

In position 13 is to  
prove the control grid.  
En position 13 vérifier  
l'action de commande de la  
grille.


654

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 3. 55

6 E 6


Triode + Triode  
Karte 653 + Karte 654



Unbrauchbar  
mauvais / Bad

?

G u t  
Good / Bon



0

10

20

30

40

50 mA