


TUNG-SOL

TRIODE-PENTODE

COMPACTRON

OUTLINE DRAWING
JEDEC 9-58BASE 12 PIN BUTTON
JEDEC E12-70MEDIUM- μ TRIODE AND BEAM PENTODE


FOR

VERTICAL-DEFLECTION OSCILLATOR
AND VERTICAL-DEFLECTION AMPLIFIER
SERVICE

IN T.V. APPLICATIONS

COATED UNIPOTENTIAL CATHODE

ANY MOUNTING POSITION

BASING DIAGRAM
JEDEC 12 DZ

THE 6JZ8 IS A MEDIUM- μ TRIODE AND A BEAM PENTODE IN THE 12 PIN COMPACTRON CONSTRUCTION. THE TRIODE IS DESIGNED FOR SERVICE AS A VERTICAL-DEFLECTION OSCILLATOR AND THE PENTODE AS A VERTICAL-DEFLECTION AMPLIFIER IN TELEVISION RECEIVERS.

DIRECT INTERELECTRODE CAPACITANCES

WITHOUT EXTERNAL SHIELD

PENTODE SECTION

GRID 1 TO PLATE (g TO p)	0.34 pf
INPUT: G ₁ TO (H + K + G ₂ + G ₃)	11 pf
OUTPUT: P TO (H + K + G ₂ + G ₃)	7.0 pf

TRIODE SECTION

GRID TO PLATE (G TO P)	3.6 pf
INPUT: G TO (H + K)	2.2 pf
OUTPUT: P TO (H + K)	0.7 pf

CONTINUED ON FOLLOWING PAGE

TUNG-SOL

CONTINUED FROM PRECEDING PAGE

HEATER CHARACTERISTICS AND RATINGS

DESIGN MAXIMUM VALUE - SEE EIA STANDARD RS-239

AVERAGE CHARACTERISTICS	6.3 VOLTS	1,200	MA
LIMITS OF APPLIED VOLTAGE		6.3 ± 0.6	VOLTS
HEATER-CATHODE VOLTAGE:			
DC COMPONENT		100	VOLTS
TOTAL DC AND PEAK		200	VOLTS
HEATER NEGATIVE WITH RESPECT TO CATHODE			
TOTAL DC AND PEAK		200	VOLTS

MAXIMUM RATINGS

DESIGN MAXIMUM RATINGS - SEE EIA STANDARD RS-239

	TRIODE SECTION	PENTODE SECTION	
	VERTICAL OSCILLATOR ^A SERVICE	VERTICAL DEFLECTION ^A AMPLIFIER SERVICE	
PLATE VOLTAGE - DC	250	250	VOLTS
PEAK PULSE PLATE VOLTAGE		2,000	VOLTS
GRID 2 VOLTAGE		200	VOLTS
PEAK NEGATIVE GRID 1 VOLTAGE	400	150	VOLTS
PLATE DISSIPATION	1.0	7.0 ^B	WATTS
GRID 2 DISSIPATION		1.8	WATTS
CATHODE CURRENT - DC	20	70	MA
PEAK CATHODE CURRENT	70	245	MA
GRID 1 CIRCUIT RESISTANCE			
WITH FIXED BIAS	1.0	1.0	MEGOHMS
WITH CATHODE BIAS	2.0	2.0	MEGOHMS

^A FOR OPERATION IN A 525 - LINE, 30 - FRAME TELEVISION SYSTEM AS DESCRIBED IN "STANDARDS OF GOOD ENGINEERING PRACTICE CONCERNING BROADCAST STATIONS", FEDERAL COMMUNICATIONS COMMISSION. THE DUTY CYCLE OF THE VOLTAGE PULSE MUST NOT EXCEED 15% OF ONE SCANNING CYCLE.

^B IN STAGES OPERATING WITH GRID-LEAK BIAS, AN ADEQUATE CATHODE-BIAS RESISTOR OR OTHER SUITABLE MEANS IS REQUIRED TO PROTECT THE TUBE.

CONTINUED ON FOLLOWING PAGE

TUNG-SOL

CONTINUED FROM PRECEDING PAGE

CHARACTERISTICS AND TYPICAL OPERATION

	TRIODE SECTION		PENTODE SECTION		
PLATE VOLTAGE	150		45	120	VOLTS
GRID 2 VOLTAGE			110	110	VOLTS
GRID 1 VOLTAGE	-5,0		0 ^C	-8,0	VOLTS
PLATE CURRENT	5,5		122	46	MA
GRID 2 CURRENT			16,5	3,5	MA
AMPLIFICATION FACTOR	20				
TRANSCONDUCTANCE	2,350			7,100	μ MHOS
PLATE RESISTANCE - APPROX.	8,5			11,7	KOHMS
GRID 1 VOLTAGE FOR $I_b = 10 \mu A$ APPROX.	-11			-25	VOLTS

C APPLIED FOR SHORT INTERVAL (2 SECONDS) SO AS NOT TO DAMAGE TUBE.