



Betriebsdaten:
 Typical operation:
 Exemple d'utilisation:

	485	484
U_f	3	2,8 V
I_f	1,25	1,6 A
U_a	+180	+180 V=
U_{g1}	-9	-9 V=
I_a	6	6 mA
S	1,35	1,35 mA/V
D	8	8 ‰
g	12,5	12,5
R_i	9,3	9,3 kΩ

Grenzdaten:
 Ratings: / Conditions maxima:
 U_{fk} . . . 90 . . . 90 V

Prüfdaten:

Test operation:

Vérification:

U_f . . . 3 V_~

U_a . . . +150 V=

U_{g1} . 0 & -2 V=

In Stellung 13
 auf Steuerwirkung
 prüfen

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

523

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 4. 55.

485

484


484 A

Triode.

Unbrauchbar
 mauvais / Bad

?

G u t
 Good / Bon



0

5

10

15

20

25 mA