

**Betriebsdaten:**

Typical operation:

Exemple d'utilisation:

$U_f$  . . . . 6,3 V  
 $I_f$  . . . . 0,85 A  
 $U_a$  . . . . +250 V=  
 $U_{g1}$  . . . . -25 V=  
 $I_a$  . . . . 3,7 mA  
 $S$  . . . . 0,33 mA/V  
 $D$  . . . . 16,7 %  
 $g$  . . . . 6  
 $R_i$  . . . . 19 k $\Omega$

**Grenzdaten:**

Ratings: / Conditions maxime:

$U_a$  . . . . +285 V=  
 $N_a$  . . . . 1 W  
 $U_{fk}$  . . . . 90 V

**Prüfdaten:**

Test operation:

Vérification:

$U_f$  . . . . 6,3 V $\sim$   
 $U_a$  . . . . +150 V=  
 $U_{g1}$  . 0 & -2 V=

In Stellung 13  
auf Steuerwirkung  
prüfen

In position 13 is to  
prove the control grid.  
En position 13 vérifier  
l'action de commande de la  
grille.

747

Patent-Röhrenprüfer Modell W19


MAX FUNKE, Adenau-Eifel 3. 55.

**6 AD 7**

6 AD 7 G

6 AD 7 GT



Pentode + **Triode**  
Karte 562 + Karte 747



Unbrauchbar  
mauvais / Bad

?

**G u t**  
Good / Bon



2,5 mA