

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 6,3 V
 I_f . . . 0,3 A
 U_a . . . +95 V=
 U_{g1} . . . -15 V=
 I_a . . . 7 mA
 S . . . 1,2 mA/V
 D . . . 24 %
 g . . . 4,2
 R_i . . . 3,5 k Ω
 R_{fk} . . . 2140 k Ω

Grenzdaten:

Ratings: / Conditions maxima:

U_a . . . +300 V=
 P . . . 2,5 W

 U_{fk} . . . 90 V

Prüfdaten:

Test operation:

Vérification:

U_f . . . 6,3 V~
 U_a . . . +60 V=
 U_{g1} 0 & -2 V=

**In Stellung 13
auf Steuerwirkung**

prüfen

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

731

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 3, 55

6 AE 5

6 AE 5 G 6 AE 5 GT/G

6 AE 5 GT

Triode.

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon

