

**Betriebsdaten:**

Typical operation:

Exemple d'utilisation:

U_f 6,3 V
 I_f 0,15 A
 U_a . . . +250 V=
 U_{g1} . . -1,5 V=
 I_a . . . 6,5 mA
 S 1,0 mA/V
 D 4 %
 g 25
 R_i 25 k Ω

Grenzdaten:

Ratings: / Conditions maxima:

U_a . . . +250 V=
 U_{ik} . . . 90 V

Prüfdaten:

Test operation:

Vérification:

U_f . . . 6,3 V~
 U_a . . . +200 V=
 U_{g1} . 0 & -2 V=

**In Stellung 13
auf Steuerwirkung**

prüfen

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

686

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 4. 55.



6 AE 6**6 AE 6 G**

Triode + Triode
 Karte 686 + Karte 687

Unbrauchbar
 mauvais / Bad

?

G u t
 Good / Bon

**10 mA**