



Betriebsdaten:
 Typical operation:
 Exemple d'utilisation:

U_f . . . 6,3 V
 I_f . . . 0,3 A
 U_a . . +250 V=
 U_{g1} . . -9 V=
 I_a . . . 4,5 mA
 S . . . 1,25 mA/V
 D . . . 5 %
 g . . . 20
 R_i . . . 16 k Ω

Grenzdaten:
 Ratings / Conditions maxima:

U_a . . +300 V=
 N_a . . . 2,5 W
 U_{fk} . . 90 V



Prüfdaten:

Test operation:

Verification:

U_f . . . 6,3 V~
 U_a . . +150 V=
 U_{g1} 0 & -2 V=

**In Stellung 13
 auf Steuerwirkung**

prüfen

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

593

Patent-Röhrenprüfer Modell W 19


MAX FUNKE, Adenau-Eifel 4. 55

6 C 7

85 AS

85 A-S

Triode + Duodiode
 Karte 593 + Karte 521



85 AS


Unbrauchbar
 mauvais / Bad

?

G U T
 Good / Bon



6 C 7



25 mA