

Betriebsdaten:
Typical operation:
Exemple d'utilisation:

U_f . . . 6,3 V
 I_f . . . 0,15 A
 U_a . . . +250 V=
 U_{g1} . . . -9 V=
 I_a . . . 8 mA
 S . . . 1,9 mA/V
 D . . . 6 %
 g . . . 17
 R_i . . . 9 k Ω

Grenzdaten:
Ratings: / Conditions maxima:
 U_{fk} . . . 90 V

Prüfdaten:

Test operation:

Vérification:

U_f . . . 6,3 V~
 U_a . . . +150 V=
 U_{g1} . . . 0 & -2 V=

**In Stellung 13
 auf Steuerwirkung**

prüfen

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

656

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 3. 55


6 L 5	6 L 5 MG
6 L 5 G	VT-213
6 L 5 GT	VT-213 A

Triode.

Unbrauchbar
 mauvais / Bad

?

G u t
 Good / Bon



25 mA

