

**Betriebsdaten:**

Typical operation:

Exemple d'utilisation:

$U_f$  . . . 1,4 V  
 $I_f$  . . . 0,05 A  
 $U_a$  . . . +90 V=  
 $U_g$  . . . -3 V=  
 $I_a$  . . . 3 mA  
 $S$  . . . 1,1 mA/V  
 $D$  . . . 8,5 %  
 $g$  . . . 12

**Prüfdaten:**

Test operation:

Vérification:

$U_f$  . . . 1,0 V~  
 $U_a$  . . . +60 V=  
 $U_g$  . . . 0 & -2 V=

In Stellung 13  
auf Steuerwirkung  
prüfen

In position 13 is to  
prove the control grid.  
En position 13 vérifier  
l'action de commande de la  
grille.

232

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 7. 53.

**DC 90**

UKW-Triode

Unbrauchbar  
mauvais / Bad

?

**G u t**  
Good / Bon

0


1

2

3

4

5 mA

**Grenzdaten:**

Ratings: / Conditions maxima:

$U_a$  . . . +90 V=  
 $I_k$  . . . 5 mA  
 $R_g$  . . . 3 M $\Omega$   
 $N_a$  . . . 0,6 W

