

Betriebsdaten:
 Typical operation:
 Exemple d'utilisation:

EBC 91 / 6 AV 6 | 6 AT 6

U _f	...	6,3	..	6,3	V
I _f	...	0,3	..	0,3	A
U _a	...	+250	+	250	V=
U _g	...	-2	..	-3	V=
I _a	...	1,2	..	1	mA
S	...	1,6	..	1,2	mA/V
D	...	1	..	1,4	%
g	...	100	..	70	
R _i	...	62	..	58	kΩ

Prüfdaten:
 Test operation:
 Vérification:

U_f . . . 6,3 V~
 U_a . . +150 V=
 U_g . 0& -2 V=

In Stellung 13
 auf Steuerwirkung
 prüfen


In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

893

Patent-Röhrenprüfer Modell **EBC 91** **w 17** MAX FUNKE, Adenau-Eifel 11. 53.

EBC 91 | 6 AT 6 EBC 90 6 AQ 6
6 AV 6 | 6 BK 6

Triode + Duodiode
 Karte 893 + Karte 894



Grenzdaten:

Ratings: / Conditions maxima:


U_a . . +250 V=
 U_{fk} . . 90 V
 I_k 4 mA
 R_{fk} . . 10 kΩ
 R_g . . . 3 MΩ
 N_a . . . 1 W
 U_{fk} . . 50 V



Unbrauchbar
 mauvais / Bad

?

G u t
 Good / Bon



5 mA