

**Betriebsdaten:**

Typical operation:

Exemple d'utilisation:

$U_f$  . . . 6,3 V  
 $I_f$  . . . 0,3 A  
 $U_a$  . . +100 V=  
 $U_{g1}$  . . . 0  
 $S$  . . . . 3 mA/V  
 $D$  . . . . 6 %  
 $g$  . . . . 17

**Prüfdaten:**

Test operation:

Vérification:

$U_f$  . . . 6,3 V~  
 $U_a$  . . +100 V=  
 $U_g$  . 0 & -2 V=



In Stellung 13  
auf Steuerwirkung

prüfen

In position 13 is to  
prove the control grid.  
En position 13 vérifier  
l'action de commande de la  
grille.

943

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 7, 54.

**ECF 12**

Triode + Pentode  
Karte 943 + Karte 944

**Grenzdaten:**

Ratings: / Conditions maxime:


$U_a$  . . +150 V=  
 $R_g$  . . . . 1 M $\Omega$

$N_a$  . . . . 1 W  
 $U_{fk}$  . . 100 V

Unbrauchbar  
mauvais / Bad

?

**G u t**  
Good / Bon



10 mA

