

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 6,3 V
 I_f . . . 0,23 A
 U_a . . . +100 V=
 U_g . . . 0
 I_a . . . 10 mA
 S . . . 2,8 mA/V
 D . . . 4,5 %
 g . . . 22
 R_i . . . 8 k Ω

Prüfdaten:

Test operation:

Vérification:

U_f . . . 5,3 V~
 U_a . . . +100 V=
 U_{g1} . . . 0 & -2 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

928

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 4. 54.


ECH 42 | ECH 43 | ECH 113

Triode + Hexode
Karte 928 + Karte 929


Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon



10 mA

**Grenzdaten:**

Ratings: / Conditions maxima:

U_a . . . +175 V=
 I_k . . . 6 mA

R_{fk} . . . 20 k Ω
 R_g . . . 3 M Ω
 N_a . . . 0,8 W
 U_{fk} . . . 50 V

