

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 6,3 V
 I_f . . . 0,2 A
 U_a . . . +250 V
 U_{g1} . . . -2 V=
 U_{g2} . . . +100 V=
 I_a . . . 3 mA
 I_{aw} . . . 0,9 mA
 I_{g2} . . . 1 mA
 I_{g2w} . . . 0,3 mA
 S 2,1 mA/V
 R_i . . . 1500 k Ω
 R_{aw} . . . 200 k Ω
 R_{g2w} . . . 500 k Ω
 R_k . . . 500 Ω
 R_{kw} . . . 3000 k Ω

Grenzdaten:

Ratings / Conditions maxima:

U_a . . . +300 V=
 U_{g2} . . . +200 V=
 R_k 10 mA
 R_{fk} 20 k Ω
 R_{g1} 3 M Ω
 N_a . . . 1,5 W
 N_{g2} . . . 0,4 W
 U_{fk} . . . 100 V

Prüfdaten:

Test operation:

Vérification:

U_f . . . 6,3 V~
 U_a . . . +200 V=
 U_{g1} . . . 0 Δ -2 V=
 U_{g2} . . . +100 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

249

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 4. 54.

EF 12
EF 12 K




EF 12 spez.

Pentode.

Unbrauchbar
mauvais / Bad


?

G u t
Good / Bon



EF 12

EF 12 spez.



10 mA