

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 6,3 V
 I_f . . . 0,4 A
 U_a . . +250 V=
 U_{g1} . . -2 V=
 U_{g2} . +100 V=
 U_{g3} . . 0
 I_a . . . 4,5 mA
 I_{g2} . . . 1,6 mA
 S . . . 2,2 mA/V
 R_i . . . 1400 k Ω
 R_k . . . 330 Ω

**Prüfdaten:**

Test operation:

Vérification:

U_f . . . 6,3 V~
 U_a . . +200 V=
 U_{g1} . 0 & -2 V=
 U_{g2} . +100 V=
 U_{g3} . . . 0

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

113

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 10. 54.

EF 2

Pentode, regelbar / Variable mu pentode / Pentode à pente variable.

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon

0


2

4

6

8

10 mA

**Grenzdaten:**

Ratings / Conditions maxima:

U_a . . +300 V=
 U_{g2} . +125 V=
 R_{fk} . . 20 k Ω
 R_{g1} . . . 2 M Ω
 N_a . . . 1,5 W
 N_{g2} . . 0,3 W
 U_{fk} . . 100 V