

Betriebsdaten:
 Typical operation:
 Exemple d'utilisation:

| EF 93 | 6 CB 6 |
|--------------------|----------------------|
| U_f . . . 6,3 | . . . 6,3 V |
| I_f . . . 0,3 | . . . 0,3 A |
| U_a . + 250 | +200 V= |
| U_{g1} . . -1 | -2,2 V= |
| U_{g2} . +100 | +150 V= |
| U_{g3} . . . 0 | . . . 0 |
| I_a . . . 11 | . . . 9,5 mA |
| I_{g2} . . . 4,2 | . . . 2,8 mA |
| S . . . 4,4 | . . . 6,2 mA/V |
| R_i . . . 1500 | . . . 600 k Ω |
| R_k . . . 68 | . . . 180 Ω |
| R_{g2} . . . 33 | . . . k Ω |

Grenzdaten:
 Ratings: / Conditions maxima:

| | |
|-------------------|------------------|
| U_a . + 300 | +300 V= |
| U_{g2} . +125 | +150 V= |
| I_k . . . 18 | . . . mA |
| R_{fk} . . . 10 | . . . k Ω |
| R_g . . . 2 | . . . M Ω |
| N_a . . . 3 | . . . 2 W |
| N_{g2} . 0,6 | . . . 0,5 W |
| U_{fk} . 50 | . . . 90 V |

Prüfdaten:
 Test operation:
 Vérification:

| | |
|-----------------------|----------|
| U_f . . . 6,3 | V \sim |
| U_a . . . +200 | V= |
| U_{g1} . . . 0 & -2 | V= |
| U_{g2} . . . +60 | V= |
| U_{g3} . . . 0 | |


In Stellung 13
 auf Steuerwirkung
 prüfen
 In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

895

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 7. 53.

| | | |
|---|---------------|----------------------------|
| EF 93 | 6 BA 6 | 6 CB 6 |
| Pentode, regelbar / Variable mu pentode / Pentode à pente variable. | | |
| Unbrauchbar mauvais / Bad | ? | G u t Good / Bon |



EF 93 / BA 6

6 CB 6



10 mA

