


Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f	. . .	6,3 V
I_f	. . .	1,9 A
U_a	. . .	+500 V=
U_{g1}	. . .	-22 V=
U_{g2}	. . .	+500 V=
I_a	. . .	95 mA
I_{g2}	. . .	12,5 mA
S	. . .	11 mA/V
R_i33 k Ω
R_k	. . .	200 Ω

**Prüfdaten:**

Test operation:

Vérification:

U_f	. . .	6,3 V~
U_a	. . .	+200 V=
U_{g1}	. . .	0 & -2 V=
U_{g2}	. . .	+150 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

468

Patent-Röhrenprüfer Modell W 19


MAX FUNKE, Adenau-Eifel 2. 55.

EL 51

End-Pentode / Output Pentode / Pentode de puissance.

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon

0


10

20

30

40

50 mA

**Grenzdaten:**

Ratings / Conditions maxima:

U_a	. . .	+750 V=
U_{g2}	. . .	+750 V=
I_k	. . .	200 mA
R_{fk}	. . .	5 k Ω
R_{g1}	. . .	0,7 M Ω
N_a	. . .	45 W
N_{g2}	. . .	7 W
U_{fk}	. . .	50 V