

Betriebs daten :
 Typical operation :
 Exemple d'utilisation :

EZ 40/113 | **7 Z 4**

U_f	.. 6,3	.. 6,3 V
I_f	.. 0,6	.. 0,9 A
U_a max	350	.. 325 V eff
I_a max	.. 90	.. 100 mA
R_a	.. min 300	.. 75 Ω
U_{fk} max	500	.. 425 V
C	.. max 50	.. 40 μF



EZ 113

Prüf daten :
 Test operation :
 Vérification :

U_f . . . 6,3 V \sim
 U_a . . . 60 V \sim

Röhre hat 2 Systeme.
 Das 2. System ist in
 Stellung 13 zu messen.
 2. System is measurable
 in position 13
 2. System est à prouver
 en position 13

960

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel — 4-53

EZ 40 Mazda VG 1	EZ 113 EZ 41	7 Z 4 7 Z 4-GL VT-181
----------------------------	------------------------	------------------------------------

Doppelweg-Gleichrichter / Rectifier / Redresseur



EZ 40




7 Z 4

Unbrauchbar
 Inutile / Bad

?

G u t
 Good / Bon



50 mA

