

Betriebsdaten:

Typical operation:
Exemple d'utilisation:

U_f 2 V=
 I_f 0.21 A
 U_a +135 V=
 U_g -2,8 V=
 I_a 3 mA
 S 2,5 mA/V
 D 3,3 %
 g 30
 R_i 12 k Ω

**Prüfdaten:**

Test operation:
Vérification:

U_f 2 V \sim
 U_a +100 V=
 U_g 0 & -2 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

121

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 2. 55.

KC 3

Triode.

Grenzdaten:

Ratings: / Conditions maxima:




U_a +150 V=
 I_k 7 mA

R_g 1,5 M Ω
 N_a 1 W

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon



10 mA