



Betriebsdaten:
 Typical operation:
 Exemple d'utilisation:

	2204	E 409
U _f . . .	4	4 V
I _f . . .	2,2	1 A
U _a . . .	+200	+200 V=
U _{g1} . . .	-10	-16 V=
I _a . . .	15	12 mA
S . . .	3	1,3 mA/V
D . . .	10	11 %
g . . .	10	9
R _i . . .	3,5	7 kΩ
R _k . . .	667	1330 kΩ

Grenzdaten:
 Ratings: / Conditions maxima:
 N_a . . . 3 | 3 W

Prüfdaten:
 Test operation:
 Vérification:

U_f . . . 4 V~
 U_a . . . +150 V=
 U_{g1} 0 & -2 V=

In Stellung 13
 auf Steuerwirkung
 prüfen

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 4. 55.

Telefunken REN 2204	Valvo LK 4100 L 4100	Philipps E 408 E 409 E 409 N
Triode.		
Unbrauchbar mauvais / Bad	?	G u t Good / Bon

