



Betriebsdaten:
 Typical operation:
 Exemple d'utilisation:

	914	1004	4100
U _f	4	4	4 V
I _f	1,2	1,1	0,9 A
U _a	+200	+200	+150 V=
U _g	-1,5	-5	-1 V=
I _a	1	0,04	4 mA
S	2,5	0,02	1,5 mA/V
D	1	3	3,3 %
g	100	33	30
R _i	40		20 kΩ
R _a		1000	kΩ
R _k	1,5		kΩ

Patent-Röhrenprüfer Modell W19

Prüfdaten:

Test operation:

Vérification:

U_i . . . 4 V~
 U_a . . . +200 V=
 U_{g1} . 0 & -2 V=

In Stellung 13
 auf Steuerwirkung
 prüfen

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

35

Grenzdaten:

Ratings / Conditions maxima:

	914	1004
U _a	+250	+200 V=
R _g	1	MΩ
I _k	15	mA
Na	1,5	W

MAX FUNKE, Adenau-Eifel 4. 55.

Telefunken	Valvo	Tungsram	Philipps
REN 914	W 4110	AR 4120	E 499
REN 1004	W 4080	AR 4101	E 438 N
	W 4100	AR 4100	E 430
		AR 495	

Triode.



Unbrauchbar
 mauvais / Bad

?

G u t
 Good / Bon

