



Betriebsdaten:

Typical operation:


Exemple d'utilisation:

- U_f 4 V
- I_f 1,8 A
- U_a . . . +350 V=
- U_{g1} . . -3,5 V=
- U_{g2} . . +150 V=
- I_a 30 mA
- I_{g2} . . . 4,5 mA
- S 10 mA/V
- D 4,5 %

Grenzdaten:

Ratings: / Conditions maxima:

- U_a . . . +400 V=
- U_{g2} . . +200 V=
- I_g 10 mA
- N_a 10 W
- N_{g2} . . . 2,5 W
- η 8 W



Prüfdaten:

Test operation:

Vérification:

- U_f 4 V~
- U_a . . . +200 V=
- U_{g1} . . 0 & -2 V=
- U_{g2} . . +100 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 2. 55


RS 288

Sende-Pentode / Transmitting pentode / Pentode d'émission.

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon



50 mA

