

Betriebsdaten:
 Typical operation:
 Exemple d'utilisation:

U_f . . . 26 V
 I_f . . . 0,1 A
 U_a . . . +170 V=
 U_g . . . -1,5 V=
 I_a . . . 10 mA
 S . . . 6,2 mA/V
 D . . . 2 %
 g . . . 50

Prüfdaten:
 Test operation:
 Vérification:

U_f . . . 24 V~
 U_a . . . +150 V=
 U_g . 0 & -2 V=

**In Stellung 13
 auf Steuerwirkung
 prüfen**

In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.


556

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 3. 54.

UCC 85

Triode + Triode
 Karte 556 + Karte 644



Grenzdaten:

Ratings: / Conditions maxima:


U_a . . +300 V=
 I_k . . . 20 mA
 R_{fk} . . . 20 k Ω
 R_g . . . 1 M Ω
 N_a . . . 2,5 W
 U_{fk} . . . 90 V



Unbrauchbar
 mauvais / Bad

?

G u t
 Good / Bon



25 mA