

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 20 V
 I_f . . . 0,1 A
 U_a . . +100 V=
 U_g . . -2,4 V=
 I_a . . . 5 mA
 S 2 mA/V
 D . . . 5,3 %
 g . . . 19
 R_i . . . 9 k Ω

Prüfdaten:

Test operation:

Vérification:

U_f . . . 20 V \sim
 U_a . . +100 V=
 U_g . . 0 $\&$ -2 V=

825



**In Stellung 13
auf Steuerwirkung
prüfen**


In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 5. 54.

UCH 4

Hexode + **Triode**
Karte 347 + Karte 825

**Grenzdaten:**

Ratings: / Conditions maxima:

U_a . . +175 V=
 I_k . . . 5 mA
 N_a . . . 0,5 W
 R_g . . . 3 M Ω

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon



0

5

10

15

20

25 mA