

T.			$U_z$	$U_{stab}$	$I_4$	$I_3$	$I_2$	$I_1$	$I_{min+max}$
			V	V	mA	mA	mA	mA	mA
RT 260/40	LMT	1	340	235 ÷ 280	15	40	60	80	10 ÷ 40
RT 260/80	LMT	1	340	235 ÷ 280	60	80	80	90	15 ÷ 80
RT 300/40	LMT	1	370	290 ÷ 335	15	40	60	80	10 ÷ 40
RT 300/80	LMT	1	370	290 ÷ 335	60	80	80	90	15 ÷ 80
STV 280/40	eur	1	340	270 ÷ 290	15	40	60	80	10 ÷ 40
STV 280/40 Z	eur	2	302	270 ÷ 290	15	40	60	80	10 ÷ 40
STV 280/80	eur	1	340	270 ÷ 290	60	80	80	90	15 ÷ 80
STV 280/80 Z	eur	2	302	270 ÷ 290	60	80	80	90	15 ÷ 80
STV 280/150	eur	3	335	270 ÷ 300					40 ÷ 150
STV 280/150 Z	eur	2	302	270 ÷ 300					40 ÷ 150
STV 600/200	STV	4	680	550 ÷ 610					50 ÷ 200

1) vido \* 4

2)  $U_z = 420$  V,  $I_4 = 35$  mA,  $I_3 = 40$  mA,  $I_2 = 60$  mA,  $I_1 = 60$  mA,  $I_{min} = 5$  mA

3)  $U_z = 420$  V,  $I_4 = 70$  mA,  $I_3 = 70$  mA,  $I_2 = 90$  mA,  $I_1 = 100$  mA,  $I_{min} = 10$  mA

Equivalents

OSW 3806	RFT = STV 280/40	StR 280/80 Z	RFT = STV 280/80 Z
OSW 3807	RFT = STV 280/40 Z	STV 280/40 <sup>1)</sup>	Marc = STV 280/40
OSW 3808	RFT = STV 280/80	STV 280/40 A <sup>1)</sup> 2)	GEC = STV 280/40
OSW 3809	RFT = STV 280/80 Z	STV 280/40 B <sup>1)</sup> 2)	GEC = STV 280/40
PTT 3001 <sup>1)</sup>	LMT = STV 280/40	STV 280/80 <sup>3)</sup>	GEC = STV 280/80
PTT 3002 <sup>1)</sup>	LMT = STV 280/80	STV 280/80 A <sup>1)</sup> 3)	GEC = STV 280/80
RT 280/40 <sup>1)</sup>	LMT = STV 280/40	STV 280/80 B <sup>1)</sup> 3)	GEC = STV 280/80
RT 280/80 <sup>1)</sup>	LMT = STV 280/80	STV 280/150 Z/II	STV = STV 280/150 Z
StR 280/40	RFT = STV 280/40	STV 600/200/III	STV = STV 600/200
StR 280/40 Z	RFT = STV 280/40 Z	11 TF 25	Tes = STV 280/40
StR 280/80	RFT = STV 280/80	12 TF 25	Tes = STV 280/80

