

**Betriebsdaten:**

Typical operation:

Exemple d'utilisation:

$U_f$  . . . 6,3 V  
 $I_f$  . . . 0,3 A  
 $U_a$  +12,6 V=  
 $U_{g1}$  . . . 0 V=  
 $R_{g1}$  . . . 47 k $\Omega$   
 $I_a$  . . . 0,75 mA  
 $S$  . . . 1,4 mA/V

**Prüfdaten:**

Test operation:

Vérification:

$U_f$  . . . 6,3 V~  
 $U_a$  . . . +30 V=  
 $U_{g1}$  . 0 & -2 V=

In Stellung 13  
auf Steuerwirkung  
prüfen

In position 13 is to  
prove the control grid.  
En position 13 vérifier  
l'action de commande de la  
grille.

1028

Röhrenmeßgerät Modell W 19

MAX FUNKE, Adenau-Eifel 4. 58.

**ECH 83**

Triode + Hexode  
Karte 1028 + Karte 1029

Unbrauchbar  
mauvais / Bad

?

**G u t**  
Good / Bon



0


1

2

3

4

5 mA

**Grenzdaten:**

Ratings: / Conditions maxima:

$U_a$  . . . +30 V=  
 $I_k$  . . . 3 mA  
 $R_{g1}$  . . . 3 M $\Omega$

