

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 12,6 V
 I_f . . . 0,1 A
 U_a . . . +200 V=
 U_{g1} . . . -2 V=
 U_{g2} . . . +85 V=
 U_{g3} . . . 0
 I_a . . . 5 mA
 I_{g2} . . . 1,5 mA
 S . . . 1,8 mA/V
 R_i . . . 1300 k Ω
 R_k . . . 310 Ω
 R_{g2} . . . 76 k Ω

Grenzdaten:

Ratings: / Conditions maxima:

U_a . . . +250 V=
 U_{g2} . . . +150 V=
 I_k . . . 10 mA
 R_{fk} . . . 20 k Ω
 R_{g1} . . . 3 M Ω
 N_a . . . 2 W
 N_{g2} . . . 0,3 W
 U_{fk} . . . 150 V

Prüfdaten:

Test operation:

Vérification:

U_f . . . 12,6 V~
 U_a . . . +200 V=
 U_{g1} . . . 0 & -2 V=
 U_{g2} . . . +60 V=
 U_{g3} . . . 0

In Stellung 13
auf Steuerwirkung

prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

915

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 4, 54.

UAF 41

D 121

UAF 42



WD 142

Diode + Pentode
Karte 914 + Karte 915

Unbrauchbar
mauvais / Bad


?

G u t
Good / Bon



UAF 41

UAF 42



10 mA