



# ECL 85

## Pentode Triode



Neval B9A



$J_A$  - Bereich

A

### $J_A$ 150 mA



170 V



300

$U_{III}$



$G_2$



$G_1$



$U_I$



170 V

$A_T$

$G_T$

$K_T$



F



F



$K_S$



#### Meßspannungen

Heizung	F	6,3	V
$U_I$	$G_1$	6	-V
$U_{II}$			-V
$U_{III}$	$G_2$	170	V
$U_{IV}$			V
A		170	V

#### Richtströme

$J_A$	150	mA
$J_{G_2}$		mA
S		mA/V

### Heizung 6,3 Volt

Meßkarte für NEUBERGER Röhrenmeßgeräte